TUNING IN THE PRE-PROGRAMMED NETWORKS

For the Manhattan Skyline 1000 FTA Receiver

These instructions are only for sites that purchased the Manhattan Skyline Receiver from 3ABN or another supplier of the Manhattan 1000. These instructions assume your dish is already at AMC 4 (aka GE 4) and bringing in a signal. After you are sure the dish is pointing at the correct satellite and the signal is as strong as possible you are ready to add the ATN/ACN settings and search for the channel. (The signal bar will turn green when you are locked into the correct satellite).

Press the **MENU** button on the remote to see this screen.

1. OSD Setup
2. TV Setings
3. Time Settings
4. VCR Timer Settings
5. Master Reset
6. System Information

Press the **RIGHT ARROW** here

1. Antenna Settings
2. Channel Search
3. Favorite Channels
4. Parental Lock

Use the **UP** or **DOWN ARROW** to highlight Channel Search then press **OK**.

CHANNEL SEARCH

Search Index	1
Antenna	1
Satellite	AMC 4 (101.0W)
Search Mode	Auto All
TP Data	TPI:3ABN
LNB Skew	.45
Positioner	None

START

At the satellite line the name should be AMC 4 or GE 4.

Highlight the TP Data line. Press OK to set up a new network.

TP2: User Defined

Freq:	**11983**
Polarity	**Horz.**
S/R	**05900**
FEC	**AUTO**
Video PID	0000
Audio PID	0000
PCR PID	0000

STORE

Press the Right Arrow until User Defined shows up. This allows you to set up a new network.
Highlight the Freq line and enter 11983
Highlight Polarity and select Horz.
Highlight S/R and enter 05900
Highlight FEC and make sure it says AUTO

Highlight STORE and press OK.

After the new information stores, you will return to the setup/search screen.